

DATA SHEET



CHINA

ADSL POTS Distributed Filter DSL261

RoHS compliant.
Compact package.
Ease of installation.
High quality low pass filter
with optimum performance.
Removes radio interference on the line.
CE compliant.

Specifications

Return lost reference Impedance	600Ω	Insulation resistance	> 10 MΩ
Insertion Loss @ 1kHz	< 0.3dB	High Freq. Insertion Loss	
Insertion Loss distortion 200 to 3.4KHz	< 1.0dB	25KHz to 30KHz	> 55dB
Return Loss 300Hz to 500Hz	> 14dB(SRL-L)	30KHz to 300KHz	> 65dB
500Hz to 2000Hz	> 18dB (ERL)	300KHz to 12KHz	> 55dB
2000Hz to 3400Hz	> 14dB (SRL-H)		
Group Delay Distortion @ 300 -3.400 KHz	< 150μs	Ringing Frequency	
DC Resistance	< 25Ω	15.3KHz to 68KHz	
DC Current Range	18mA~120mA		

